

Example of that used on Boland models

4K24-12G, 4K55-12G.

Applies to:

BVB

PVB

LVB

1. RS-232 straight through pinout.

Baud rate - 9600

Parity bit - none

Data Bit - 8

Stop Bit - 1

Handshake - none

RS-232 Codes:

4k models:

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x0a - SDI 1

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x0b - SDI 2

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x0c - QUAD

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x0d - 2SI

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x08 - HDMI

HD models, too:

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x0f - CVBS 1

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x01 - CVBS 1

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x02 - CVBS 2

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x03 - CVBS 3

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x04 - S-VIDEO

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x05 - RGB

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x06 - Y-Pb-Pr

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x07 - PC

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x08 - HDMI

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\x01\x09 - DVI

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\xfe\x00 - Display off

\x51\x42\x54\x4d\xf5\x8a\x0a\xfe\xfe\x01 - Display on

2. Network control - IP address of the unit and use Port 5009.

Use RS-232 codes data.