



2. Transmission data code table

2.1 Key Function Codes

CUSTOM CODE: 30CFH+

Red FUNCTIONS below are currently inactive.

MONITOR FUNCTIONS	KEY NO.	FUNCTION	DATA CODE
☆	K1	SOFT POWER TOGGLE	17
	K2	ATTENTION	0B
	K3	1	0D
	K4	2	0E
	K5	3	0F
	K6	4	16
	K7	5	1D
	K8	6	1E
	K9	7	1F
	K10	8	04
	K11	9	05
	K12	AV/TV	05
	K13	0/+10	07
☆	K14	MUTE	0C
	K15	CH +	09
☆	K16	ZOOM	10
☆	K17	VOL +	11
	K18	CH -	42
☆	K19	PIP	00
	K20	VOL - -	14
☆	K21	▲	19
☆	K22	◀ -	15
☆	K23	▶ +	12
☆	K24	▲	8
☆	K25	MENU BACK	1C
☆	K26	MENU DISPLAY-EXIT	1A
☆	K27	MENU NEXT	59
	K28	REPEAT	5E
☆	K29	FREEZE	5D
☆	K30	S-VIDEO	5C
☆	K31	PC VGA RGB	18
☆	K32	VGA (SD YCrCb)	58
☆	K33	COMPOSITE 1	5A

Note: Attn and 1 (in sequence) toggles IR on/off.
Attn and 2 (in sequence) enables BL menu.

Unassigned Codes: 5d, 5e

11/06/14/mb

HD SDI 1	61	SFP1	65
HD SDI 2	62	SFP2	66
HD YPbPr	60	DispPort1	?? --> 67
DVI1	63	DVI2	?? --> 69
COMPOSITE2	5B	VGA2	?? --> 6A
Soft Power ON	20	Comp3	?? --> 6B
Soft Power OFF	21	Comp4	?? --> 6C
HDMI	64	DispPort2	?? --> 68