

Power Consumption by Model max power shown when in full brite or HDR mode* **boland**

	Model Name	Power Consumption		
		Voltage	Current	W
1	4K17c-12G	12V	3.83A	46W
2	4K24c-12G, TE	24V	3.75A	90W
3	4K31-12G, TE	24V	3.34A	80W
4	4K49c-12G	24V	4.58A	110W
5	4K55c-12G, TE	24V	5A	120W
6	4K65c-12G	24V	5.84A	140W
7	4K75c-12G	24V	10.41A	250W
8	BVB07a	12V	1.67A	20W
9	BVB09a	12V	2.08A	25W
10	BVB16DB	12V	2.08A	25W
11	BVB17	12V	3.34A	40W
12	BVB17a	12V	3.34A	40W
13	BVB17DB	12V	5A	60W
14	BVB17_OLED	28V	2.5A	70W
15	BVB24	12V	5.42A	65W
16	BVB24a	12V	5.42A	65W
17	BVB24b	24V	5.42A	65W
18	BVB25_OLED	28V	3.21A	90W
19	BVB32	24V	5.84A	140W
20	BVB42	24V	5.29A	127W
21	BVB49	24V	6.08A	146W
22	BVB55	24V	6.67A	160W
23	BVB55_OLED	24V	12.5A	300W
24	BHB12HDR15	12V	2.5A	30W
25	BHB16HDR12	12V	5A	60W
26	BHB17HDR	12V	3.34A	40W
27	BHB24HDR4_NE	24V	2.08A	50W
28	BHB24HDR15	12V	6.83A	82W
29	BHB26HDR4	24V	2.91A	70W
30	BHB32HDR4, TE	24V	2.7A	65W
31	BHB42HDR7	24V	4.37A	105W
32	BHB49HDR5	24V	4.16A	100W
33	LVB17 & LVB17-G	12V	3.75A	45W

	Model Name	Power Consumption		
		Voltage	Current	W
35	LVB21, TE	12V	3.34A	40W
36	LVB23, -LD, -G	12V	3.34A	40W
37	LVB27	12V	3.34A	40W
38	PVB15	12V	3.34A	40W
39	PVB16LDB	12V	5A	60W
40	PVB17 & PVB17a	12V	3.34A	40W
41	PVB20a	12V	3.75A	45W
42	PVB20a_TE	12V	3.75A	45W
43	PVB20b_TE	12V	3.34A	40W
44	PVB20c, TE	12V	3.34A	40W
45	PVB24a, TE	12V	5.42A	65W
46	PVB27	12V	3.34A	40W
47	PVB32a, TE	24V	2.91A	70W
48	PVBL20	12V	3.75A	45W
49	PVBL24, -GC	12V	5.42A	65W
50	TP08	12V	1.25A	15W
51	TP10	12V	2.08A	25W
52	TP12DB	12V	1.91A	23W
53	TP15_TS	12V	2.08A	25W
54	TP15DB	12V	2.08A	25W
55	TP17DB	12V	3.16A	38W
56	TP19DB	12V	2.91A	35W
57	4k17HDR4	12V	3.34A	40W
58	4k24HDR3	24V	3.75A	90W
59	4k31HDR3	24V	3.34A	80W
60	4k31HDR10	24V	6.67A	160W
61	4K43HDR3	24V	2.92A	70W
62	4K49HDR5, TE	24V	4.58A	110W
63	4k55HDR5	24V	4.16A	100W
64	4K65HDR5	24V	5.84A	140W
65	4K75HDR	24V	10.42A	250W
66	4K98HDR5	24V	22.92A	550W
67	4k65OLED	24V	16.67A	400W

*Indoor operation power is typically half that shown (factory calibrated to SMPTE 100 nts/Rec 709).